



## **STEPHILL GENERATORS LTD 5000HM/ES**

### **5.0kVA "HIRE-MAX" RANGE PORTABLE PETROL GENERATING SET (3000rpm)**

<b>OUTPUT:</b>	5.0kVA (4.0kW), 50Hz, 115/230v, single phase.
<b>CONTROL BOX:</b>	Alternator top mounted metal control box comprising 1 x 16a & 1 x 32a 115v, 2x230v/16a BS4343 socket outlets, changeover switch & re-set button circuit breakers.
<b>ENGINE:</b>	Honda GX270 electric start, single cylinder air cooled petrol engine with "oil alert" low oil level shutdown, fitted with fuel tank and exhaust silencer.
<b>ALTERNATOR:</b>	Markon brushless maintenance free, smooth waveform alternator, single bearing.
<b>FUEL TANK:</b>	6.0 litre fuel tank giving 3.5 hours operation at 75% load
<b>FRAME:</b>	1" heavy duty tubular steel wrap-around frame with battery box
<b>MOUNTS:</b>	Anti-vibration mounts.
<b>NOISE LEVEL:</b>	71dBA @ 7 metres. 96 LWA
<b>DIMENSIONS:</b>	L690 x W480 x H540mm
<b>WEIGHT:</b>	70kg (dry).